

IL-M-20125

20 Amp Manual Reset User Attachable Inline GFCI



SPECIFICATIONS

Attribute	Value
Product Weight	~0.5 lbs.
Shipping Volume	~66 in ³
Accepts Cordage	12awg-3c
Current (Amps)	20 Amps
Temperature Low (C)	-35
Temperature High (C)	66
Trip Level (mA)	4-6 mA
Voltage (Volts)	120V
Reset Type	Manual
Color	Black

COUNTRIES OF APPLICATION

COUNTRY	RELEVANT APPROVAL	COUNTRY	RELEVANT APPROVAL
---------	-------------------	---------	-------------------

United States : East

+1 860-763-2100

sales@worldcordsets.com

210 Moody Road, Enfield, CT, 06082